

| DataRate | Configuration |
|----------|-----------------------|
| 0 | LoRa:SF12/125kHz |
| 1 | LoRa:SF11/125kHz |
| 2 | LoRa:SF10/125kHz |
| 3 | LoRa:SF9/125kHz |
| 4 | LoRa:SF8/125kHz |
| 5 | LoRa:SF7/125kHz |
| 6 | LoRa:SF7/250kHz |
| 7 | FSK:50 kbps |
| 8...14 | RFU |
| 15 | Keep Current DataRate |

| TXPower | Configuration(EIRP) |
|---------|----------------------|
| 0 | Max EIRP |
| 1 | Max EIRP - 2dB |
| 2 | Max EIRP - 4dB |
| 3 | Max EIRP - 6dB |
| 4 | Max EIRP - 8dB |
| 5 | Max EIRP - 10dB |
| 6...14 | RFU |
| | |
| | |
| 15 | Keep Current TXPower |

| ChMask | |
|--------|-----------------|
| Bit | Usable channels |
| 0 | Channel 1 |
| 1 | Channel 2 |
| ... | ... |
| 15 | Channel 16 |

| ChMaskCntl | ChMask applies to |
|------------|-------------------|
| 0 | Channels 1 to 16 |
| 1...5 | RFU |
| 6 | All channels ON |
| 7 | RFU |