

High-Density Coding Scheme for SWIPT Systems

Dongheon Lee, Gyuyeol Kong, Jang-Won Lee, and Sooyong Choi

Abstract—A novel coding scheme called high-density coding using high-density codebook generated from a genetic local search algorithm is proposed. The high-density codebook maximizes the energy transfer capability by maximizing the ratio of 1 in the codebook which satisfies the conditions of a codeword with length n , a codebook with 2^k codewords, and a minimum Hamming distance of the codebook of d . Furthermore, the proposed high-density codebook provides a trade-off between throughput and harvested energy with respect to n , k , and d . The block error rate performance of the designed high-density codebooks are derived theoretically and compared with the simulation results. The simulation results indicate that as d or k decrease or n increases, the throughput decreases whereas the harvested energy increases. With the proposed high-density coding scheme, the throughput and the harvested energy at the user can be controlled adaptively according to the system requirements.

Index Terms—encoding, high-density coding, simultaneous wireless information and power transfer (SWIPT).

I. INTRODUCTION

IN the era of Internet of Things (IoT), the role of wireless devices is emerging [1]. To prolong the lifetime of the IoT network, batteries of wireless devices must be replaced or recharged. However, the management of batteries for a large number of wireless devices is expensive and inconvenient [2]. Therefore, simultaneous wireless information and power transfer (SWIPT) systems have received an extensive amount of interest to achieve the efficient power management of batteries. Studies on SWIPT systems have been conducted for various areas, such as the design of a waveform [3] or precoder [2], [4], and channel coding [5], [6], [7].

In particular, the coding scheme for SWIPT systems differ from the conventional coding schemes for wireless information transfer (WIT) systems which only consider the information transfer performance such as data rate or block error rate (BLER). The conventional channel coding schemes from Hamming code to low-density parity-check (LDPC) codes which have been widely used for WIT systems do not consider the performance of the energy harvesting (EH). In wireless power transfer systems wherein the signal transmission time and power are critical, EH performance degradation occurs when the conventional coding method is used. Therefore, to improve the EH performance of the channel coding scheme in SWIPT systems, several studies have been conducted [5], [6], [7].

Unary-coded SWIPT transceiver was analyzed from an information theoretical perspective in [5]. In [6], run-length-limited (RLL) encoder was designed to minimize the battery overflow/underflow probability at a receiver subject to a constraint on the achievable mutual information. Moreover, the capacity lower bound of the binary symmetric channel and Z-channel was determined in [7] when RLL code was adopted.

Most of the research on coding schemes for SWIPT systems is based on systems using on-off keying (OOK) modulation.

The OOK modulation uses two types of signals, namely ‘on’ and ‘off,’ because analog modulation schemes are considered to be efficient for SWIPT systems [10]. Analog modulation schemes do not require a local oscillator or an analog to digital converter, which consume relatively high power; moreover, OOK modulation is the simplest modulation among analog modulations [10]. The ratio of the ‘on’ signal to the ‘off’ signal is critical for EH because energy harvesters can only harvest energy from the ‘on’ signal. Therefore, controlling a ratio of 1 is vital in codeword design. To increase the number of 1’s in a codeword, the unary code and RLL code were developed in [5], [6]; these codes are a type of variable length code requiring complex decoding algorithms [11].

In this paper, we propose a high-density channel coding scheme and a high-density codebook design algorithm for SWIPT systems using OOK modulation. The proposed high-density codebook design algorithm produces a fixed-length codebook that can decode with a lower complexity than that in the case of RLL code or unary code based on a genetic algorithm. For the WIT systems, there are papers which apply the genetic algorithm to a channel coding [8], [9]. The genetic algorithm was used to optimize the position of the frozen bits in polar codes producing an A-vector as an output [8]. In [9], the genetic algorithm was used to optimize the edges between the variable nodes and the check nodes in LDPC codes producing a generator matrix as an output. An output of the genetic algorithm used in this paper is a codebook which satisfies the following two conditions: maximization of the ratio of 1 in the codebook and preservation of the minimum Hamming distance between the codewords in the codebook to deal with both the BLER performance and the EH performance. Therefore, we use a unique crossover and a mutation process suitable for our purpose.

The proposed high-density codebook can be obtained using a genetic local search algorithm that comprises three steps, namely local search, recombination, and final selection. In the local search step, a genetic local search algorithm produces codewords that satisfy the given condition, such as the length of the codeword, number of codewords in the codebook, and minimum Hamming distance in the codebook. The recombination step generates new codebooks by transforming the codebooks from the local search step. The final selection step selects the codebook with the maximum number of 1’s. Therefore, the proposed coding scheme can increase the duration of actual transmitted radio frequency (RF) signals and maintain the throughput of information transmission while achieving performance gain in terms of harvested energy.

In addition, the proposed high-density codebooks demonstrate a trade-off between the throughput and harvested energy performance based on various codebook design parameters such as codeword length, number of codewords in the code-




Fig. 1: Receiver for both ID and EH.

book, and minimum Hamming distance of the codebook. Therefore, it is possible to transmit a signal adaptive to conditions such as the data and energy requirements of the receiver and the bit error rate constraint of the systems.

II. SYSTEM MODEL

We consider single-input single-output SWIPT systems using OOK modulation. An access point (AP) transmits the OOK signal, and both the AP and receiver comprise the codebook information and BLER table of each codebook based on the signal-to-noise ratio (SNR). An AP transmits the OOK signals used at the receiver for information decoding (ID) and EH, as illustrated in Fig. 1. Fig. 1 depicts the receiver structure considered in this paper. The received signal at the antenna is converted into a DC signal using a rectifier. Because the RF to DC conversion in the rectifier is analogous to the RF band to baseband conversion, a mixer that consumes high energy is not required for ID [12].

To analyze the relationship between the BLER and harvested energy among the codebooks in the additive white Gaussian noise channel, we consider the received signal at the receiver as

$$y = x + z,$$


where $x \in \{0, \sqrt{2 \cdot E_b}\}$ denotes the OOK signal with a bit energy E_b and $z \sim \mathcal{N}(0, N_0/2)$ denotes the identically distributed additive Gaussian noise. In addition, it is assumed that the maximum likelihood (ML) decoding for soft decisions is used for the codeword estimator. Then, the codebook can be expressed as (n, k, d) with W , where n denotes the length of the codeword in the codebook, 2^k denotes the number of codewords in the codebook, d denotes the minimum Hamming distance between two different codewords in the codebook, and W denotes the number of 1's in the codebook. The performance metrics of the codebook can be both throughput and harvested energy. The throughput for the (n, k, d) codebook system can be defined as

$$\eta_{n,k,d} = (k/n) \times (1 - P_{n,k,d}),$$

where $P_{n,k,d}$ is the BLER of the (n, k, d) codebook. The theoretical BLER of the designed (n, k, d) codebook from the proposed high-density codebook design algorithm can be given by

$$P_{n,k,d} \approx \sum_{i=0}^{2^k-1} \frac{1}{2^k} \cdot A_{d,i} \cdot Q\left(\sqrt{d \cdot \frac{E_b}{N_0}}\right), \quad (1)$$

where $A_{d,i}$ denotes the number of codewords that have the Hamming distance d with the i th codeword in the codebook.

Fig. 2: Codeword selection methods for $(3, 2, d)$ codebook (a) $W = 9, d = 1$ and (b) $W = 6, d = 2$.

Additionally, the encoded bits are transmitted in the communication system using OOK modulation, where a digital bit 1 indicates the presence of a carrier wave and digital bit 0 indicates the absence of a carrier wave. Therefore, the number of 1's represents the number of transmissions and determines the EH performance. The harvested energy for the (n, k, d) codebook system can be measured in two ways: $Q_{n,k,d}^b = n_{n,k,d}/k$, $Q_{n,k,d}^t = n_{n,k,d}/n$, where $Q_{n,k,d}^b$ denotes the harvested energy per bit, $Q_{n,k,d}^t$ denotes the harvested energy per time, and $n_{n,k,d}$ denotes the number of 1's in the (n, k, d) codebook.

In this paper we proposed a coding scheme called high-density coding. High-density coding encodes k bits into n bits of as many 1's as possible satisfying the minimum hamming distance condition k of the codebook which is generated from the proposed genetic local search based algorithm. Fig. 2 illustrates an example of the trade-off between the number of 1's and the minimum Hamming distance. In Fig. 2, the codewords with the largest number of 1's satisfying the condition of minimum Hamming distance d are selected to construct the $(3, 2, d)$ codebook. The EH performance of the codebook depicted in Fig. 2a is better than that of the codebook depicted in Fig. 2b while the BLER performance of the codebook depicted in Fig. 2b is better than that of the codebook depicted in Fig. 2a.

III. PROPOSED CODEBOOK DESIGN ALGORITHM

We propose a high-density coding scheme that uses a codebook with the maximum number of 1's for maximizing the harvested energy while satisfying the minimum Hamming distance of the codebook for maintaining error correction capability. However, in general, designing a codebook for a given (n, k, d) is an NP-hard problem that is challenging, particularly for large values of n , k , and d [13]. In addition to the (n, k, d) condition, we consider the performance gain of the harvested energy by maximizing the number of 1's in the codebook. Therefore, designing a codebook that satisfies all the conditions is even more challenging. To this end, a high-density codebook design algorithm using a genetic local search algorithm was proposed.

A. Genetic Local Search-Based High-Density Codebook

In this subsection, we introduce the high-density codebook design algorithm for SWIPT systems. The codebook design algorithm based on the genetic local search algorithm constructs a codebook with the maximum number of 1's while




Fig. 3: Parameter mapping between coding scheme and genetic algorithm for $(3, 2, 1)$ codebook.

maintaining the minimum distance between the codewords. Fig. 3 depicts a relationship between the parameters of the coding scheme and genetic algorithm. The population of the genetic local search algorithm comprises a set of codebooks. The codebook and codeword correspond to the chromosome and gene in a conventional genetic algorithm, respectively.

The genetic local search algorithm begins by generating an initial population P_{input} and then modifies the population at each step. First, the population P increases by applying the local search procedure to each codebook C in P . Next, the enlarged population P' is generated by producing child codebooks through the application of a recombination procedure to the population P . The population P' increases by applying the local search procedure to each codebook C in P' , and a certain number of best codebooks are selected. The RECOMBINATION, second LOCAL SEARCH, and SELECTION algorithms are repeated until the stop criterion is satisfied. The entire algorithm is summarized in Algorithm 1. In the following, we describe the details of the genetic local search algorithm.

1) *Initial population*: The initial population P_{input} in the genetic local search algorithm is randomly generated. The initial population comprises a fixed number of codebooks. Each codebook consists of a number of codewords between 1 and $2^k - 1$, satisfying the minimum Hamming distance d . Owing to the complexity of generating the initial population, it is preferable not to generate an excessively large number of codewords in the initial population. On the contrary, if there are extremely few codewords in the initial population, sufficient population diversity cannot be achieved.

2) *Local search*: In this step, we describe a local search procedure in Algorithm 1 which extends the input codebooks to obtain a large number of codewords. The codebook, which includes a large number of codewords, exhibit a high probability of the selected k codewords having a large number of 1's. Because the local search procedure is operated by satisfying the minimum distance between the codebooks, the codebook design condition for minimum distance can be maintained.

At first, the mutation procedure is applied to the codebook C at position S which denotes the position indicator in the codeword. Next, when the input codebook is C , from $x = 0$ to $x = 1$, $d(x, C)$ which denotes the Hamming distance between x and C can be calculated in each iteration. When $d(x, C) \geq d$, C is extended by including x . When $d(x, C) \leq d$, x becomes $x + 1$. The extending procedure is

Algorithm 1 GENETIC LOCAL SEARCH

Input: Initial population P_{input}
 $P = P_{input}$
for all $C \in P$ **do**
 $C = \text{LOCAL SEARCH}(C)$
end for
repeat
 $P' = \text{RECOMBINATION}(P)$
 for all $C \in P'$ **do**
 $C = \text{LOCAL SEARCH}(C)$
 $P = P \cup \{C\}$
 end for
 $P = \text{SELECTION}(P)$
until STOP

Algorithm 2 LOCAL SEARCH

Input: Codebook C_{input} , Positions S
 $C = C_{input}$
 $C' = \text{mutation}(C, S) \triangleleft$ bit flip at the positions S in C
 $x = 0$
repeat
 if $d(x, C') \geq d$ **then**
 $C' = C' \cup \{x\}$
 end if
 $x = x + 1$
until $x = 1$
 $C = \text{mutation}(C', S)$

repeated until $x = 1$. If C is extended in this manner, any y which is larger than x in lexicographical ordering exhibits a smaller Hamming distance to C than d . Therefore, extending the codebook suffices to continue the procedure with $x + 1$.

For a given input codebook C , the codebook-extending procedure always yields the same extended codebook. Therefore, for a variety of population, a process that generates a new codebook C' transformed from codebook C , the so-called mutation, is required. In the mutation process, the positions in the codebook with a length of n are randomly selected, and the bits in the selected positions for every codeword in the codebook C are modified by swapping the values 1 and 0 with each other. Because the mutation does not affect the (n, k, d) property of the codebook C , the codebook C is equivalent to the transformed codebook C' . After applying the local search algorithm to C' , the inverse of the mutation applied to codebook C is applied to the output of the codebook extension procedure. Applying the inverse of the mutation process causes the extended codebook to include the input codebook C . The local search algorithm is summarized in Algorithm 2.

3) *Recombination*: In this step, a new codebook is generated from the output codebook of the LOCAL SEARCH algorithm. Recombination is the most significant process for a local genetic search algorithm for achieving a sub-optimal solution. Recombination extends the search area and therefore increases the diversity of the population.

We assume that all input populations for RECOMBINATION have the same p even number of codewords. We first select $p/2$ pairs of parent codebooks from the input population P_{input} , such that codebooks with a large number of 1's are selected as a parent codebook with a higher probability. If the number of codewords m in the i^{th} codebook

Algorithm 3 RECOMBINATION

Input: Population P_{input}
 $P = P_{input}$
 $P' = \{\}$
 $i = 1$
repeat

 select $C_1, C_2 \in P$

 produce C'_1 and C'_2
 $P' = P' \cup \{C'_1, C'_2\}$
 $i = i + 1$
until $i = p/2$

is smaller than 2^k , the number of 1's in the i^{th} codebook multiplied by $2^k/m$ represents the weight W_i of the codebook. Otherwise, the number of 1's represents the weight W_i of the codebook. If W_{min} is the minimum weight among W_i , $i \in \{1, \dots, p\}$, the i^{th} codebook is selected as a parent with probability p_i written as $p_i = 1/c \times (W_i - W_{min} + 1)$, where $c = \sum_{j=1}^p (W_j - W_{min} + 1)$. Next, we combine the two codebooks to produce the child codebooks.

Theorem 1: Let C_j and C_k be two codebooks with length n and a minimum Hamming distance of at least d . Let \mathbf{a} be a codeword in \mathbb{Z}^n , and D be an integer with $0 \leq D \leq n + d$. Then,

$$\{\mathbf{x} \in C_j | d(\mathbf{x}, \mathbf{a}) \leq D - d\} \cup \{\mathbf{x} \in C_k | d(\mathbf{x}, \mathbf{a}) \geq D\}$$

is a codebook with length n and a minimum Hamming distance of at least d .

Proof: Let \mathbf{x}_1 be a codeword from the codebook $\{\mathbf{x} \in C_j | d(\mathbf{x}, \mathbf{a}) \leq D - d\}$ and \mathbf{x}_2 be a codeword from the codebook $\{\mathbf{x} \in C_k | d(\mathbf{x}, \mathbf{a}) \geq D\}$. To ensure that $d(\mathbf{x}_1, \mathbf{x}_2)$ is smaller than d , $|d(\mathbf{x}_1, \mathbf{a}) - d(\mathbf{x}_2, \mathbf{a})|$ should be smaller than d . However, the minimum value of $|d(\mathbf{x}_1, \mathbf{a}) - d(\mathbf{x}_2, \mathbf{a})|$ is d when $d(\mathbf{x}_1, \mathbf{a})$ has the largest value $D - d$, and $d(\mathbf{x}_2, \mathbf{a})$ has the smallest value of D . ■

According to the above theorem, the produced child codebooks have the same length and minimum Hamming distance as those of the parent codebooks. Let C_1 and C_2 be a selected parent pair of codebooks; select the codeword \mathbf{a} and integer D that satisfy the conditions of length n and $0 \leq D \leq n + d$. According to C_1 , C_2 , \mathbf{a} , and D , the two child codebooks C'_1 and C'_2 are generated as follows:

$$C'_1 = \{\mathbf{x} \in C_1 | d(\mathbf{x}, \mathbf{a}) \leq D - d\} \cup \{\mathbf{x} \in C_2 | d(\mathbf{x}, \mathbf{a}) \geq D\},$$

$$C'_2 = \{\mathbf{x} \in C_2 | d(\mathbf{x}, \mathbf{a}) \leq D - d\} \cup \{\mathbf{x} \in C_1 | d(\mathbf{x}, \mathbf{a}) \geq D\}.$$

Then, we include C'_1 and C'_2 in a new population p' . The selection of parent codebooks and generation of child codebooks are repeated until the $p/2$ pair of child codebooks are produced. Therefore, p child codebooks can be generated from p parent codebooks. The recombination algorithm is summarized in Algorithm 3.

4) *Selection:* In the SELECTION step, p codebooks are selected, which can serve as the input codebooks for the subsequent iteration of the algorithm, from the p parent codebooks in population P and p child codebooks in population P' . If there is no codebook with more than 2^k codewords, we select the p codebooks that have the largest W_i . If there are more than $p/2$ codebooks with more than 2^k codewords, we select $p/2$




Fig. 4: BLER performance with varying SNR. (a) Difference in the minimum Hamming distance, d . (b) Difference in the number of codewords, 2^k .

codebooks that have the largest W_i among the codebooks that have more than 2^k codewords, and select the remaining $p/2$ codebooks that have the largest W_i among the codebooks that have less than 2^k codewords. If there are q ($\leq p/2$) codebooks with more than 2^k codewords, we select q codebooks with more than 2^k codewords and select the remaining $p - q$ codebooks that have the largest W_i among the codebooks with less than 2^k codewords.

5) *Stop criterion:* After the selection of the codebooks, the stop criterion decides whether to repeat or stop the local genetic search algorithm. If there are codebooks with more than 2^k codewords, we stop the algorithm until the maximum codebook weight among the codebooks in a population does not change in a certain number of iterations. If there is no codebook with more than 2^k codewords, we stop the algorithm until the maximum number of codewords among the codebooks in a population does not change in a certain number of iterations.

IV. SIMULATION RESULTS

The (n, k, d) codebooks using the proposed high-density codebook design algorithm are evaluated in terms of the BLER with the theoretical results and the proposed high-density coding is evaluated in SWIPT systems. The number of codebooks for the initial population and number of selected codebooks in each iteration p are 10. The number of codewords in each codebook is randomly determined between 1 and 5.

In Fig. 4a, the $(10, 3, 3)$, $(10, 3, 4)$, and $(10, 3, 5)$ codebooks are evaluated in terms of the BLERs for the simulation and theoretical results according to various SNRs for different minimum Hamming distances d with fixed values of n and k . Fig. 4a depicts that the BLER decreases as the minimum Hamming distance in the codebook increases, the difference between the likelihoods of the codewords in ML decoding increases. In Fig. 4b, the $(10, 3, 3)$, $(10, 4, 3)$, and $(10, 5, 3)$ codebooks are evaluated in terms of the BLERs for the simulation and theoretical results according to various SNRs for different numbers of codewords 2^k with fixed values of n and d . Fig. 4b depicts that the BLER increases as the number of codewords 2^k increases. As the number of codeword pairs with a minimum Hamming distance increases, the number of detection errors in ML decoding increases.




Fig. 5: Performance trade-off between throughput $\eta_{n,k,d}$ and harvested energy $Q_{n,k,d}^b$ and $Q_{n,k,d}^t$. (a) With the difference in the minimum Hamming distance d . (b) With the difference in the number of codewords 2^k . (c) With the length of codeword n .

In Figs. 5a, the (10,3,3), (10,3,4), and (10,3,5) codebooks are evaluated in terms of throughput and harvested energy for different minimum Hamming distances d with fixed values of n and k , respectively. The (10,3,3) codebook yields the highest performance in terms of harvested energy and lowest performance in terms of throughput. In contrast, the (10,3,5) codebook yields the lowest performance in terms of harvested energy and highest performance in terms of throughput. As d decreases, throughput increases since BLER decreases while harvested energy increases since the number of 1's in the proposed high-density codebook increases.

In Fig. 5b, the (10,3,4), (10,4,4), and (10,5,4) codebooks are evaluated in terms of throughput and harvested energy, respectively, for different numbers of codewords 2^k with fixed values of n and d . The (10,3,4) codebook yields the highest performance in terms of harvested energy and lowest throughput performance. In contrast, the (10,5,4) codebook yields the lowest performance in terms of harvested energy and highest performance in terms of throughput. As k decreases, throughput increases since code rate increases while harvested

energy decreases since the proposed codebook from the high-density codebook design algorithm comprises codewords that have a relatively fewer number of 1's to satisfy the minimum Hamming distance condition.

In Fig. 5c, the (7,4,3), (8,4,3), (9,4,3), and (10,4,3) codebooks are evaluated in terms of throughput and harvested energy, respectively, for different codeword lengths n with fixed values of k and d . The (10,4,3) codebook yields the highest performance in terms of harvested energy and lowest performance in terms of throughput. In contrast, the (7,4,3) codebook yields the lowest performance in terms of harvested energy and highest performance in terms of throughput. As n increases, throughput decreases since code rate decreases while harvested energy increases since the number of 1's in the proposed high-density codebook increases as n increases.

V. CONCLUSIONS

In this paper, we proposed a high-density coding scheme that can control throughput and harvested energy in a given channel using a genetic local search-based high-density codebook design algorithm that generates a high-density codebook. We designed codebooks that satisfy the given (n,k,d) condition, which is in general an NP-hard problem, and analyzed throughput and harvested energy performance according to the variation in the (n,k,d) condition in the theoretical results. The simulation results revealed a trade-off between throughput and harvested energy. In addition, throughput increased and harvested energy decreased as k increased, whereas throughput decreased and harvested energy increased as n and d increased.

REFERENCES

- [1] M. O. Ojo *et al.*, "A review of low-end, middle-end, and high-end IoT devices," *IEEE Access*, vol. 6, pp. 70528-70554, 2018.
- [2] R. Zhang and C. K. Ho, "MIMO broadcasting for simultaneous wireless information and power transfer," *IEEE Trans. Wireless Commun.*, vol. 12, no. 5, pp. 1989-2001, May 2013.
- [3] B. Clerckx and E. Bayguzina, "Waveform design for wireless power transfer," *IEEE Trans. Signal Process.*, vol. 64, no. 23, pp. 6313-6328, Dec. 2016.
- [4] D. Lee *et al.*, "SCLNR-Based Precoding Scheme for Multi-User MIMO SWIPT Systems," *IEEE Trans. on Veh. Technol.*, vol. 68, no. 12, pp. 12392-12395, Dec. 2019.
- [5] J. Hu *et al.*, "Unary Coding Controlled Simultaneous Wireless Information and Power Transfer," *IEEE Trans. on Wireless Commun.*, vol. 19, no. 1, pp. 637-649, Jan. 2020.
- [6] A. M. Fouladgar *et al.*, "Constrained codes for joint energy and information transfer," *IEEE Trans. Commun.*, vol. 62, no. 6, pp. 2121-2131, Jun. 2014.
- [7] A. Tandon *et al.*, "On code design for simultaneous energy and information transfer," in *Proc. Inf. Theory Appl. Workshop (ITA)*, Feb. 2014.
- [8] A. Elkelesh *et al.*, "Decoder-tailored polar code design using the genetic algorithm," *IEEE Trans. Commun.*, vol. 67, no. 7, pp. 4521-4534, Jul. 2019.
- [9] A. Elkelesh *et al.*, "Decoder-in-the-loop: Genetic optimization-based LDPC code design," *IEEE Access*, vol. 7, pp. 141161-141170, 2019.
- [10] S. Claessens *et al.*, "Enhanced biased ASK modulation performance for swipt with awgn channel and dual-purpose hardware," *IEEE Trans. Microw. Theory Techn.*, vol. 66, no. 7, pp. 3478-3486, Jul. 2018.
- [11] S. Malinowski *et al.*, "Synchronization recovery and state model reduction for soft decoding of variable length codes," *IEEE Trans. Inf. Theory*, vol. 53, no. 1, pp. 368-377, Jan. 2007.
- [12] X. Zhou *et al.*, "Wireless information and power transfer: Architecture design and rate-energy tradeoff," *IEEE Trans. Commun.*, vol. 61, no. 11, pp. 4754-4767, Nov. 2013.
- [13] I. Dumer *et al.*, "Hardness of approximating the minimum distance of a linear code," *IEEE Trans. Inf. Theory*, vol. 49, no. 1, pp. 22-37, Jan. 2003.