

## Isotropic

## Non-Isotropic

### Forward process

$$q_t(\mathbf{x}_t | \mathbf{x}_0) = \mathcal{N}(\sqrt{\bar{\alpha}_t} \mathbf{x}_0, (1 - \bar{\alpha}_t) \mathbf{I})$$

$$\Rightarrow \mathbf{x}_t = \sqrt{\bar{\alpha}_t} \mathbf{x}_0 + \sqrt{1 - \bar{\alpha}_t} \boldsymbol{\epsilon}$$

$$q_t(\mathbf{x}_t | \mathbf{x}_0) = \mathcal{N}(\sqrt{\bar{\alpha}_t} \mathbf{x}_0, (1 - \bar{\alpha}_t) \boldsymbol{\Sigma})$$

$$\Rightarrow \mathbf{x}_t = \sqrt{\bar{\alpha}_t} \mathbf{x}_0 + \sqrt{1 - \bar{\alpha}_t} \sqrt{\boldsymbol{\Sigma}} \boldsymbol{\epsilon}$$

### Score $\mathbf{s} = \nabla_{\mathbf{x}_t} \log q_t(\mathbf{x}_t | \mathbf{x}_0)$

$$\mathbf{s} = -\frac{1}{\sqrt{1 - \bar{\alpha}_t}} \boldsymbol{\epsilon}$$

$$\mathbf{s} = -\frac{1}{\sqrt{1 - \bar{\alpha}_t}} \sqrt{\boldsymbol{\Sigma}^{-1}} \boldsymbol{\epsilon}$$

### Score-matching loss

$$\ell(\boldsymbol{\theta}; t) = \mathbb{E}_{\mathbf{x}_0, \boldsymbol{\epsilon}} \|\mathbf{s} - \mathbf{s}_{\boldsymbol{\theta}}(\mathbf{x}_t, t)\|_2^2$$

$$\mathcal{L}(\boldsymbol{\theta}) = \mathbb{E}_t (1 - \bar{\alpha}_t) \ell(\boldsymbol{\theta}; t)$$

$$\mathcal{L}(\boldsymbol{\theta}) = \mathbb{E}_t (1 - \bar{\alpha}_t) \boldsymbol{\Sigma} \ell(\boldsymbol{\theta}; t)$$

### Noise-matching loss

$$\mathcal{L}(\boldsymbol{\theta}) = \mathbb{E}_{t, \mathbf{x}_0, \boldsymbol{\epsilon}} \|\boldsymbol{\epsilon} - \boldsymbol{\epsilon}_{\boldsymbol{\theta}}(\mathbf{x}_t, t)\|_2^2$$

$$\mathcal{L}(\boldsymbol{\theta}) = \mathbb{E}_{t, \mathbf{x}_0, \boldsymbol{\epsilon}} \|\boldsymbol{\epsilon} - \boldsymbol{\epsilon}_{\boldsymbol{\theta}}(\mathbf{x}_t, t)\|_2^2$$

### Sampling w/ DDPM

$$1) \hat{\mathbf{x}}_0 = \frac{1}{\sqrt{\bar{\alpha}_t}} (\mathbf{x}_t - \sqrt{1 - \bar{\alpha}_t} \boldsymbol{\epsilon}_{\boldsymbol{\theta}}(\mathbf{x}_t, t))$$

$$2) \mathbf{x}_{t-1} = \tilde{\boldsymbol{\mu}}_t(\mathbf{x}_t, \hat{\mathbf{x}}_0) + \sqrt{\tilde{\beta}_t} \mathbf{z}_t$$

$$1) \hat{\mathbf{x}}_0 = \frac{1}{\sqrt{\bar{\alpha}_t}} (\mathbf{x}_t - \sqrt{1 - \bar{\alpha}_t} \sqrt{\boldsymbol{\Sigma}} \boldsymbol{\epsilon}_{\boldsymbol{\theta}}(\mathbf{x}_t, t))$$

$$2) \mathbf{x}_{t-1} = \tilde{\boldsymbol{\mu}}_t(\mathbf{x}_t, \hat{\mathbf{x}}_0) + \sqrt{\tilde{\beta}_t} \sqrt{\boldsymbol{\Sigma}} \mathbf{z}_t$$

### Sampling w/ DDIM

$$1) \hat{\mathbf{x}}_0 = \frac{1}{\sqrt{\bar{\alpha}_t}} (\mathbf{x}_t - \sqrt{1 - \bar{\alpha}_t} \boldsymbol{\epsilon}_{\boldsymbol{\theta}}(\mathbf{x}_t, t))$$

$$2) \mathbf{x}_{t-1} = \sqrt{\bar{\alpha}_{t-1}} \hat{\mathbf{x}}_0 + \sqrt{1 - \bar{\alpha}_{t-1}} \boldsymbol{\epsilon}_{\boldsymbol{\theta}}(\mathbf{x}_t, t)$$

$$1) \hat{\mathbf{x}}_0 = \frac{1}{\sqrt{\bar{\alpha}_t}} (\mathbf{x}_t - \sqrt{1 - \bar{\alpha}_t} \sqrt{\boldsymbol{\Sigma}} \boldsymbol{\epsilon}_{\boldsymbol{\theta}}(\mathbf{x}_t, t))$$

$$2) \mathbf{x}_{t-1} = \sqrt{\bar{\alpha}_{t-1}} \hat{\mathbf{x}}_0 + \sqrt{1 - \bar{\alpha}_{t-1}} \sqrt{\boldsymbol{\Sigma}} \boldsymbol{\epsilon}_{\boldsymbol{\theta}}(\mathbf{x}_t, t)$$

### Expected Denoised

Sample  $\mathbf{x}_0^*(\mathbf{x}_t, t) = \mathbb{E}_{\mathbf{x}_0 \sim p_t(\mathbf{x}_0 | \mathbf{x}_t)} [\mathbf{x}_0]$

$$\mathbf{x}_0^*(\mathbf{x}_t, t) = \mathbf{x}_t - \sqrt{1 - \bar{\alpha}_t} \boldsymbol{\epsilon}_{\boldsymbol{\theta}^*}(\mathbf{x}_t, t)$$

$$\mathbf{x}_0^*(\mathbf{x}_t, t) = \mathbf{x}_t - \sqrt{1 - \bar{\alpha}_t} \sqrt{\boldsymbol{\Sigma}} \boldsymbol{\epsilon}_{\boldsymbol{\theta}^*}(\mathbf{x}_t, t)$$

### SDE formulation

$$d\mathbf{x} = -\frac{1}{2} \beta(t) \mathbf{x} dt + \sqrt{\beta(t)} d\mathbf{w}$$

$$p_{0t}(\mathbf{x}(t) | \mathbf{x}(0)) =$$

$$\mathcal{N}\left(\mathbf{x}(0) e^{-\frac{1}{2} \int_0^t \beta(s) ds}, (\mathbf{I} - \mathbf{I} e^{-\int_0^t \beta(s) ds})\right)$$

$$d\mathbf{x} = -\frac{1}{2} \beta(t) \mathbf{x} dt + \sqrt{\beta(t)} \sqrt{\boldsymbol{\Sigma}} d\mathbf{w}$$

$$p_{0t}(\mathbf{x}(t) | \mathbf{x}(0)) =$$

$$\mathcal{N}\left(\mathbf{x}(0) e^{-\frac{1}{2} \int_0^t \beta(s) ds}, \boldsymbol{\Sigma} (\mathbf{I} - \mathbf{I} e^{-\int_0^t \beta(s) ds})\right)$$