

S1200000 : $\mathfrak{so}(8) \rightarrow \mathfrak{u}(1) + \mathfrak{u}(1), \mathcal{N} = 1$

$V/g^2 = v \approx -12.0000000000, \quad v + (2^2 \cdot 3) = 0$

$\mathbf{8}_v \rightarrow \mathbf{1}^{++} + \mathbf{1}_{++} + 4 \times \mathbf{1} + \mathbf{1}_{--} + \mathbf{1}^{--}, \quad \mathbf{8}_{s,c} \rightarrow 2 \times \mathbf{1}_{++}^+ + 2 \times \mathbf{1}_{++}^- + 2 \times \mathbf{1}_{--}^+ + 2 \times \mathbf{1}_{--}^-$,

$\mathbf{28} \rightarrow \mathbf{1}_{++}^{++} + 4 \times \mathbf{1}^{++} + \mathbf{1}_{++}^{+-} + 4 \times \mathbf{1}_{++} + 8 \times \mathbf{1} + 4 \times \mathbf{1}_{--} + \mathbf{1}_{++}^{-+} + 4 \times \mathbf{1}^{--} + \mathbf{1}_{--}^{--}$

$m^2/m_0^2[\psi] : 4.000_1, 3.000_{2 \times 1}, 2.250_{1^{++}+1_{++}+1_{--}+1^{--}}, 1.000_1^*$

$m^2/m_0^2[\chi] : 8.000_1, 6.000_{2 \times 1}, 4.747_{1^{++}+1_{++}+1_{--}+1^{--}}, 4.500_{1^{++}+1_{++}+1_{--}+1^{--}},$

$3.936_{1^{++}+1_{++}+1_{++}+1_{--}+1_{--}}, 3.732_1, 2.166_{1^{++}+1_{++}+1_{--}+1^{--}},$

$2.000_{1^{++}+1_{++}+1_{++}+1_{++}+1_{--}+1_{--}}, 1.500_{2 \times 1}, 1.125_{1^{++}+1_{++}+1_{--}+1^{--}},$

$0.584_{1^{++}+1_{++}+1_{--}+1^{--}}, 0.500_{1_{++}^{++}+1_{++}^{+-}+1_{++}^{-+}+1_{++}^{--}}, 0.268_1,$

$0.125_{1^{++}+1_{++}+1_{--}+1^{--}}, 0.064_{1_{++}^{++}+1_{++}^{+-}+1_{++}^{-+}+1_{++}^{--}},$

$0.003_{1^{++}+1_{++}+1_{--}+1^{--}}, 0.000_{4 \times 1}$

$m^2/m_0^2[\phi] : 8.679_1^m, 8.196_1^m, 4.412_1^m, 1_{1^{++}+1_{++}+1_{--}+1^{--}}^m,$

$3.067_1^m, 2.732_1^m, 0.000_1^s, 1_{1_{++}^{++}+1_{++}^{+-}+2 \times 1_{++}+1_{++}^{--}}^m,$

$0.000_1^c, 1_{2 \times 1^{++}+2 \times 1^{++}+1_{++}^{++}+2 \times 1_{++}+2 \times 1_{++}+2 \times 1_{--}+1_{++}^{-+}+2 \times 1^{--}+1_{--}^{--}}^m,$

$0.000_1^m, 2_{2 \times 1^{++}+2 \times 1_{++}+2 \times 1_{++}+2 \times 1_{--}+2 \times 1^{--}}, -0.732_1^m,$

$-1.250_1^m, 1_{1^{++}+1_{++}+1_{--}+1^{--}}, -1.517_1^m, 1_{1_{++}^{++}+1_{++}^{+-}+1_{++}^{-+}+1_{++}^{--}},$

$-1.912_1^m, 1_{1^{++}+1_{++}+1_{--}+1^{--}}, -2.000_1^m, 4_{4 \times 1}, -2.196_1^m,$

$-2.229_1^m, 1_{1^{++}+1_{++}+1_{++}+1_{--}+1_{--}}, -2.250_1^m, 1_{1^{++}+1_{++}+1_{--}+1^{--}}$

$$M_{\alpha\beta} = \begin{pmatrix} 0 & 0 & 0 & 0 & A & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & -A & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & A & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & -A \\ A & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & -A & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & A & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & -A & 0 & 0 & 0 & 0 \end{pmatrix}$$

$M_{\dot{\alpha}\dot{\beta}} = \text{diag}(B, B, C, C, -C, -C, -B, -B)$

$A = 2^{-7/2} \log(5 + 2\sqrt{6}) \approx 0.2026242474, \quad B \approx 0.3672439845, \quad C \approx 0.0380045103$

$2A - B - C = 0$