

$$\mathbf{S1384096} : \mathfrak{so}(8) \rightarrow \mathfrak{so}(3), \mathcal{N} = 1$$

$$V/g^2 = v \approx -13.8409638236, \quad 5^{15} v^{12} -$$

$$(2^8 \cdot 3^4 \cdot 7 \cdot 53 \cdot 107 \cdot 887 \cdot 1567) v^8 +$$

$$(2^{15} \cdot 3^{17} \cdot 210719) v^4 - (2^{20} \cdot 3^{30}) = 0$$

$$\mathbf{8}_{v,s,c} \rightarrow 2 \times \mathbf{3} + 2 \times \mathbf{1}, \quad \mathbf{28} \rightarrow \mathbf{5} + 7 \times \mathbf{3} + 2 \times \mathbf{1}$$

$$m^2/m_0^2[\psi] : 3.411_{\mathbf{3}}, 3.180_{\mathbf{1}}, 2.906_{\mathbf{3}}, 1.000_{\mathbf{1}}^*$$

$$m^2/m_0^2[\chi] : 7.230_{\mathbf{1}}, 7.156_{\mathbf{1}}, 6.823_{\mathbf{3}}, 6.359_{\mathbf{1}}, 5.812_{\mathbf{3}}, 5.287_{\mathbf{3}}, 5.204_{\mathbf{3}}, 3.689_{\mathbf{1}}, 2.535_{\mathbf{3}},$$

$$2.478_{\mathbf{3}}, 1.927_{\mathbf{5}}, 1.706_{\mathbf{3}}, 1.590_{\mathbf{1}}, 1.453_{\mathbf{3}}, 1.014_{\mathbf{5}}, 0.164_{\mathbf{5}}, 0.090_{\mathbf{5}+\mathbf{3}},$$

$$0.032_{\mathbf{1}}, 0.000_{\mathbf{3}}$$

$$m^2/m_0^2[\phi] : 16.262_{\mathbf{1}}^m, 16.095_{\mathbf{1}}^m, 8.657_{\mathbf{1}}^m, 8.529_{\mathbf{1}}^m, 8.095_{\mathbf{1}}^m, 5.322_{\mathbf{3}}^m, 5.182_{\mathbf{3}}^m, 3.818_{\mathbf{5}}^m,$$

$$2.662_{\mathbf{1}}^m, 0.000_{\mathbf{3}}^s, 0.000_{\mathbf{3}}^c, 0.000_{\mathbf{5}+4 \times \mathbf{3}+2 \times \mathbf{1}}^m, -0.109_{\mathbf{5}}^m, -1.099_{\mathbf{5}}^m,$$

$$-1.396_{\mathbf{5}+\mathbf{3}}^m, -1.686_{\mathbf{1}}^m, -2.188_{\mathbf{1}}^m, -2.244_{\mathbf{3}}^m, -2.245_{\mathbf{5}}^m$$

$$M_{\alpha\beta} = \begin{pmatrix} A & 0 & 0 & 0 & 0 & B & 0 & 0 \\ 0 & C & 0 & 0 & D & 0 & 0 & 0 \\ 0 & 0 & E & 0 & 0 & 0 & 0 & F \\ 0 & 0 & 0 & E & 0 & 0 & -F & 0 \\ 0 & D & 0 & 0 & C & 0 & 0 & 0 \\ B & 0 & 0 & 0 & 0 & A & 0 & 0 \\ 0 & 0 & 0 & -F & 0 & 0 & E & 0 \\ 0 & 0 & F & 0 & 0 & 0 & 0 & E \end{pmatrix}$$

$$M_{\dot{\alpha}\dot{\beta}} = \text{diag}(G, G, G, H, H, H, I, J)$$

$$A \approx -0.1778567542, \quad B \approx -0.0851652411, \quad C \approx -0.0053764869,$$

$$D \approx 0.2813012410, \quad E \approx 0.0916166205, \quad F \approx 0.1843081336, \quad G \approx 0.2984524378,$$

$$H \approx 0.0007244824, \quad I \approx -0.4438492241, \quad J \approx -0.4536815367$$

$$A - B - E + F = 0, \quad B - D + 4E = 0, \quad C + D - E - F = 0, \quad 3G + 3H + I + J = 0$$