

$$\mathbf{S2215486} : \mathfrak{so}(8) \rightarrow \mathfrak{u}(1)$$

$$V/g^2 \approx -22.1548672930$$

$$8_{v,s,c} \rightarrow \mathbf{1}^{++} + 2 \times \mathbf{1}^+ + 2 \times \mathbf{1} + 2 \times \mathbf{1}^- + \mathbf{1}^{--},$$

$$\mathbf{28} \rightarrow 2 \times \mathbf{1}^{+++} + 3 \times \mathbf{1}^{++} + 6 \times \mathbf{1}^+ + 6 \times \mathbf{1} + 6 \times \mathbf{1}^- + 3 \times \mathbf{1}^{--} + 2 \times \mathbf{1}^{---}$$

$$m^2/m_0^2[\psi] : 5.919_1, 4.187_{1++1-}, 3.975_1, 3.933_{1++1--}, 3.178_{1++1-}$$

$$m^2/m_0^2[\chi] : 11.8381, 8.786_{1++++1---}, 8.373_{1++1-}, 7.951_1, 7.866_{1++1--}, \\ 7.371_{1++1--}, 6.357_{1++1-}, 6.200_{1++1-}, 6.134_1, 5.661_{1+++1--}, \\ 5.537_{1++1-}, 5.438_1, 4.773_{1++++1---}, 4.743_1, 4.369_{1+++1--}, \\ 4.215_{1++1-}, 4.071_{1++1-}, 3.731_1, 3.712_1, 3.600_{1++++1----}, \\ 2.456_{1++1-}, 2.385_1, 2.161_{1++++1---}, 1.882_1, 1.580_{1++1--}, 1.065_1, \\ 0.695_{1++1-}, 0.589_{1++1--}, 0.543_1, 0.445_{1++1-}, 0.245_{1++1-}, \\ 0.101_{1++1--}, 0.030_{1++++1---}, 0.027_1$$

$$m^2/m_0^2[\phi] : 17.211^m_{1++1--}, 14.488^m_{1++++1---}, 12.639^m_{1++1-}, 12.238^m_1, \\ 11.634^m_{1+++1---}, 9.320^m_{1++1--}, 8.975^m_{1++1-}, 8.921^m_1, 8.098^m_1, \\ 6.092^m_{1++1--}, 4.058^m_{1++1-}, 4.019^m_1, 3.337^m_{1++1--}, 3.240^m_{1++1-}, \\ 2.842^m_1, 1.435^m_{1++1--}, 0.728^m_{1++++1---}, 0.000^s_{2\times 1}, 0.000^c_{2\times 1}, \\ 0.000^m_{2\times 1+++3\times 1++6\times 1^++1+6\times 1^-+3\times 1--+2\times 1---}, -0.650^m_1, \\ -0.689^m_{1++1--}, -0.772^m_{1++1-}, -0.886^m_1, -1.213^m_{1++1-}, \\ -1.434^m_{1++++1----}, -2.248^m_{1++1--}, -2.287^m_1, -3.036^{m*}_1$$

$$M_{\alpha\beta} = \text{diag}(\mathbf{A}, \mathbf{B}, \mathbf{B}, \mathbf{C}, \mathbf{D}, \mathbf{D}, \mathbf{E}, \mathbf{E})$$

$$M_{\dot{\alpha}\dot{\beta}} = \begin{pmatrix} F & 0 & G & 0 & H & 0 & -H & 0 \\ 0 & I & 0 & J & 0 & H & 0 & -H \\ G & 0 & F & 0 & -H & 0 & H & 0 \\ 0 & J & 0 & I & 0 & H & 0 & -H \\ H & 0 & -H & 0 & K & 0 & L & 0 \\ 0 & H & 0 & H & 0 & K & 0 & L \\ -H & 0 & H & 0 & L & 0 & K & 0 \\ 0 & -H & 0 & -H & 0 & L & 0 & K \end{pmatrix}$$

$$A \approx 0.4838372668, \quad B \approx 0.3238477587, \quad C \approx -0.0888840497, \quad D \approx -0.2302669551, \\ E \approx -0.2910574122, \quad F \approx 0.0520501273, \quad G \approx 0.2951895455, \quad H \approx 0.1519519428, \\ I \approx -0.3015172040, \quad J \approx 0.0583777858, \quad K \approx 0.1247335383, \quad L \approx -0.2398209024 \\ A + 2B + C + 2D + 2E = 0, \quad F - G - I - J = 0, \quad G + 2I + J + 2K = 0$$