

Function definition

```
def intra_swap(beg_pos=beg, end_pos=end, UnitID=UID)
```

```
    for i = beg; i < end; i += 2
```

```
        SWAP(Q[UID][i], Q[UID][i + 1])
```

```
def inter_cphase(beg_pos=beg, end_pos=end)
```

```
    for i = beg; i < end; i += 2
```

```
        I[Q[0][i]][[i - 1]] += 1
```

```
def inter_right_cphase(beg_pos=beg, end_pos=end)
```

```
    for i = beg; i < end; i += 2
```

```
        I[Q[0][i]][Q[1][i + 1]] += 1
```

Implementation in program synthesis

```
for i = 0; i < ??*m + ??; i += 1
```

```
    // 2 consecutive cycles for inter-unit CPHASE
```

```
    int beg_left = 1, end_left = min(?? * i + ?? * m + ??, ...);
```

```
    int beg_right = 1, end_right = min(?? * i + ?? * m + ??, ...);
```

```
    flag = check_left_first_or_right_first(...);
```

```
    if (flag == 1) {
```

```
        inter_left_cphase(beg_left, end_left);
```

```
        inter_right_cphase(beg_right, end_right);
```


```
    } else { // do right cphase before left cphase }
```

```
    // 1 cycle for intra-unit SWAP
```

```
    int beg_u = (i + ??) mod 2, end_u = min(?? * i + ?? * m + ??, ...);
```

```
    int beg_d = beg_u, end_d = end_u;
```

```
    intra_swap(beg_u, end_u, 0); intra_swap(beg_d, end_d, 1);
```



Final solution for inter-unit QFT in Sycamore:

```
// Part I from program synthesis: CPHASE, SWAP
```

```
for i = 0; i < 2*m - 2; i += 1
```

```
    // 2 consecutive cycles for inter-unit CPHASE
```

```
    beg_left = 1; end_left = min(i + 2, 2m + 1 - i);
```

```
    beg_right = 1; end_right = min(i + 2, 2m - 2 - i);
```

```
    flag = check_left_first_or_right_first(...);
```

```
    if (flag == 1) {
```

```
        inter_left_cphase(beg_left, end_left);
```

```
        inter_right_cphase(beg_right, end_right);
```

```
    } else { ... }
```

```
    // 1 cycle for intra-unit SWAP
```

```
    beg_u = (i + 0) mod 2, end_u = min(i + 1, 2m - 2 - i);
```

```
    beg_d = beg_u, end_d = end_u;
```

```
    intra_swap(beg_u, end_u, UnitID=0);
```

```
    intra_swap(beg_d, end_d, UnitID=1);
```